

REGULACIÓN								
LED 145 S2								
P (W) Nom.	Potencia total LED más Driver(W) Real	I (mA)	4000K	3000K	2700K	2200K	1800K	PC- AMBAR
		750	20421	19813	18388	16896	14055	12665
		800	21142	20857	19561	17801	14451	13230

REGULACIÓN								
LED 145 A5								
P (W) Nom.	Potencia total LED más Driver(W) Real	I (mA)	4000K	3000K	2700K	2200K	1800K	PC- AMBAR
			20238	19635	18350	16861	13928	12551
		800	20952	20670	19520	17764	14321	13111

REGULACIÓN								
LED 145 A4								
P (W) Nom.	Potencia total LED más Driver(W) Real	I (mA)	4000K	3000K	2700K	2200K	1800K	PC- AMBAR
		750	20355	19748	18517	17015	14009	12624
		800	21073	20789	19698	17926	14403	13187

REGULACIÓN								
LED 145 A7								
P (W) Nom.	Potencia total LED más Driver(W) Real	I (mA)	4000K	3000K	2700K	2200K	1800K	PC- AMBAR
		750	19629	19044	18221	16742	13509	12174
		800	20322	20048	19383	17639	13890	12717

REGULACIÓN								
LED 145 A11								
P (W) Nom.	Potencia total LED más Driver(W) Real	I (mA)	4000K	3000K	2700K	2200K	1800K	PC- AMBAR
		750	19948	19354	18192	16716	13729	12372
		800	20652	20374	19353	17611	14116	12923

REGULACIÓN								
LED 145 A12								
P (W) Nom.	Potencia total LED más Driver(W) Real	I (mA)	4000K	3000K	2700K	2200K	1800K	PC- AMBAR
		750	20184	19582	18124	16913	13891	12518
		800	20896	20615	19280	17819	14282	13076

REGULACIÓN								
LED 145 P3								
P (W) Nom.	Potencia total LED más Driver(W) Real	I (mA)	4000K	3000K	2700K	2200K	1800K	PC- AMBAR
		750	18825	18264	17168	15775	12956	11675
		800	19489	19227	18263	16620	13321	12195