

REGULACIÓN								
LED 80 S2								
P (W) Nom.	Potencia total LED más Driver(W) Real	I (mA)	4000K	3000K	2700K	2200K	1800K	PC- AMBAR
	61	550	9375	9171	8476	7795	6532	5815
	66	600	10006	9868	9180	8395	6864	6264
	72	650	10845	10564	9883	8995	7338	6762
80	77	700	11399	11261	10329	9595	8195	7260

REGULACIÓN								
LED 80 A4								
P (W) Nom.	Potencia total LED más Driver(W) Real	I (mA)	4000K	3000K	2700K	2200K	1800K	PC- AMBAR
	61	550	9345	9141	8535	7850	6511	5796
	66	600	9973	9835	9244	8454	6841	6243
	72	650	10809	10530	9953	9058	7314	6740
80	77	700	11362	11224	10402	9662	8168	7237

REGULACIÓN								
LED 80 A30								
P (W) Nom.	Potencia total LED más Driver(W) Real	I (mA)	4000K	3000K	2700K	2200K	1800K	PC- AMBAR
	61	550	9044	8847	8281	7616	6302	5610
	66	600	9652	9519	8969	8202	6621	6043
	72	650	10462	10191	9657	8788	7079	6523
80	77	700	10996	10863	10092	9374	7906	7004

REGULACIÓN								
LED 80 P1								
P (W) Nom.	Potencia total LED más Driver(W) Real	I (mA)	4000K	3000K	2700K	2200K	1800K	PC- AMBAR
	61	550	8986	9361	8228	7567	6261	5573
	66	600	9590	9457	8911	8149	6578	6004
	72	650	10394	10125	9594	8731	7033	6481
80	77	700	10925	10793	10027	9314	7854	6959

REGULACIÓN								
LED 80 A10								
P (W) Nom.	Potencia total LED más Driver(W) Real	I (mA)	4000K	3000K	2700K	2200K	1800K	PC- AMBAR
	61	550	9354	9150	8458	7877	6518	5802
	66	600	9983	9845	9161	8483	6848	6250
	72	650	10821	10540	9863	9090	7321	6747
80	77	700	11373	11236	10308	9696	8177	7244

REGULACIÓN								
LED 80 P3								
P (W) Nom.	Potencia total LED más Driver(W) Real	I (mA)	4000K	3000K	2700K	2200K	1800K	PC- AMBAR
	61	550	8642	8454	7913	7278	6022	5360
	66	600	9223	9096	8570	7838	6327	5774
	72	650	9997	9738	9228	8398	6764	6233
80	77	700	10508	10380	9643	8958	7554	6693

REGULACIÓN								
LED 80 A5								
P (W) Nom.	Potencia total LED más Driver(W) Real	I (mA)	4000K	3000K	2700K	2200K	1800K	PC- AMBAR
	61	550	9291	9089	8458	7779	6474	5763
	66	600	9916	9779	9161	8378	6802	6208
	72	650	10748	10469	9863	8976	7272	6701
80	77	700	11297	11160	10308	9575	8121	7195

REGULACIÓN								
LED 80 A7								
P (W) Nom.	Potencia total LED más Driver(W) Real	I (mA)	4000K	3000K	2700K	2200K	1800K	PC- AMBAR
	61	550	9012	8815	8399	7724	6279	5589
	66	600	9618	9485	9096	8319	6598	6021
	72	650	10424	10154	9794	8913	7053	6500
80	77	700	10957	10824	10235	9507	7877	6979

REGULACIÓN								
LED 80 A12								
P (W) Nom.	Potencia total LED más Driver(W) Real	I (mA)	4000K	3000K	2700K	2200K	1800K	PC- AMBAR
	61	550	9266	9064	8354	7803	6456	5747
	66	600	9889	9753	9048	8404	6784	6191
	72	650	10719	10441	9741	9004	7253	6683
80	77	700	11266	11130	10181	9605	8100	7176

REGULACIÓN								
LED 80 P2								
P (W) Nom.	Potencia total LED más Driver(W) Real	I (mA)	4000K	3000K	2700K	2200K	1800K	PC- AMBAR
	61	550	9255	9053	8474	7794	6448	5740
	66	600	9877	9741	9178	8393	6775	6183
	72	650	10705	10428	9881	8993	7244	6675
80	77	700	11252	11116	10327	9593	8090	7167

REGULACIÓN								
LED 80 A6								
P (W) Nom.	Potencia total LED más Driver(W) Real	I (mA)	4000K	3000K	2700K	2200K	1800K	PC- AMBAR
	61	550	9140	8941	8369	7697	6368	5669
	66	600	9755	9620	9064	8289	6691	6107
	72	650	10573	10299	9759	8881	7154	6592
80	77	700	11113	10978	10199	9474	7989	7078